



Tuxedo Touch® Security and Smart Controller

7" Color Touchscreen Keypad with Smart Control and Voice Annunciation

The Tuxedo Touch® Controller is an innovative 7" color touchscreen keypad with smart control that helps dealers increase system add-on revenue, drive additional RMR and reduce attrition. Users can control thermostats, lights, locks, doors, garage doors and more with either 500 or 300 Z-Wave® series peripherals. The Tuxedo Touch Controller supports up to 232 Z-Wave devices.

The thin/sleek style and high resolution 7" high definition color touchscreen will look appealing in any residence or business. The ability to add pictures and videos to the home screen lets users customize it to their own preference, or dealers can add their company logo or message for increased awareness and referrals.

The intuitive menu-driven user interface and voice annunciation of alarm conditions and system status helps end-users easily control basic or advanced functions and understand system conditions. Additionally, voice annunciation gives occupants the information they need to react during an emergency...when seconds count.

Resideo can push new features or fixes directly to field installed units (Wi-Fi® has to be enabled) or allow users to update the software via the SD card slot to alleviate costly site visits. The backplate was designed to easily upgrade already installed 6160 and 6280 keypads to a Tuxedo Touch Controller, helping deliver more value to existing customers and protect from competitive takeovers.



TUXEDOW



TUXEDOWC



Side View
Less than one inch off the wall.



The home screen can display a digital picture frame featuring end-user's photos and video. Alternatively, it can display custom dealer branding images.

Tuxedo Touch® Controller Features and Technical Specifications

FEATURES

- 232 Z-Wave® 500 series controller built in (lights, thermostats, locks, garage door, water shut off, shades, etc)
- High-resolution 7" TFT display 7" WSVGA, 1024 x 600
- Thin tablet like design – less than 1" off the wall
- Intuitive touchscreen with clear identifiable icons and easy to use menu driven prompts
- Voice annunciation of system status (Ready to arm/Not ready to arm) type of alarm (Burg, Fire, CO) and zone affected
- 10 scenes that can be activated by time, day, action or conditions giving end-users the flexibility to customize to their lifestyle – view your local weather right on the homescreen
- Built-in webserver allows for local control of your Tuxedo Touch Controller through Wi-Fi® enabled devices – secondary keypad with LAN range
- Software can be updated automatically through Wi-Fi with the Auto Remote Upgrade option or via the SD card slot
- Authorized end-user can add or delete user codes (can add as many as specific panel used supports)
- View when and who used the system, track employees and temporary guests, know when family members such as daughter has disarmed the system via the event log
- View system status of each zone in zone list status screen
- Dealer can customize the homescreen with their logo or company info as well as end-users can add photos or videos to customize to their lifestyle
- End-user can easily bypass zones when trying to arm the system
- Backplate designed to easily update or retrofit current 6160 and 6280 installs
- Emulation of standard 6160 alpha display keypad
- Embedded sales video to help dealers close during the sales process and training videos to help installers and end-users with more advanced functionality like camera viewing and setting up Z-Wave devices
- Best practices video to help installers during the installation process. You can access it by scanning the below QR code with any smart phone that will take you to YouTube. We have several other best practices videos available on our YouTube channel.



SPECIFICATIONS

Dimensions:

8.0" W x 5.1" H x 0.82" D
203.2 mm W x 129.5 mm H x 20.8 mm D

Electrical:


Backlight ON, Sound ON: 12V, 270mA

Wiring (Standard four-wire connection):


Black Ground
Red +12 VDC (Aux Power)
Green "Data in" to control panel
Yellow "Data out" from control panel

Tuxedo Touch® Controller Touchscreens and Compatibility

Touchscreens



Z-Wave® List Screen



Camera Screen



Zone List Screen

Compatibility

CONTROL PANEL	MAX. NO. OF TUXEDO TOUCHSCREEN KEYPADS
VISTA-15P (Honeywell Home)	2
VISTA-15PSIA (Honeywell Home)	2
VISTA-20P (Honeywell Home)	4
VISTA-20PSIA (Honeywell Home)	4
VISTA-21iP (Honeywell Home)	4
VISTA-21iPSIA (Honeywell Home)	4
VISTA-21iPLTE (Honeywell Home)	4
VISTA-128BPT (Resideo)	6
V128BPSTIA (Resideo)	6
VISTA-250BPT (Resideo)	6
VISTA-32FBPT (Resideo)	6
VISTA-128FBPT (Resideo)	6
VISTA-250FBPT (Resideo)	6

ORDERING

TUXEDOW	7" Color Touchscreen Keypad with Smart Control and Voice Annunciation (Honeywell Home)
TUXEDOWC	7" Color Touchscreen Keypad with Smart Control and Voice Annunciation (Resideo)

For more information

resideo.com/pro



resideo

Resideo Technologies, Inc.

2 Corporate Center Drive, Suite 100

P.O. Box 9040

Melville, NY 11747

1-800-645-7492

resideo.com

L/TUXEDODLRD/D | 11/21

© 2021 Resideo Technologies, Inc.

All rights reserved.

The Honeywell Home trademark is used under license from Honeywell International Inc. These products are manufactured by Resideo Technologies, Inc. and its affiliates.